



Assembly Instructions MODO Up + Down Pendants Shades & Accessories

WARNING !

- Read all instructions before installing.
- Turn off power at main switch before installing or modifying the system.
- For installation by a qualified electrician.
- Luminaire is intended for installation in accordance with National Electric Code and local regulations. Consult with local inspector to assure compliance.
- Retain these instructions for future reference.

NOTE

- Use this instruction sheet to assemble the various components of a MODO fixture.
- Refer to the main installation sheet for installation and wiring of the fixture.

SHADE

- The shade [2] can be attached on to the main fixture [1] either before or after the fixture is installed.
- To attach the shade [2] slide it up from the bottom of the shell of the fixture [1]. Any tethers [4, 5] should be tucked inside the shade [2].
- Locate the notch on the inside rim at the top of the shade [2].
- Tip the shade [2] slightly and pass the notch over one of the three studs [3].
- Rotate the shade 120° and pass the notch over the next stud [3].
- Rotate the shade 120° again and pass the notch over the last stud [3].
- Rotate the shade 60° so the notch is approximately centered between two studs [3].
- The shade will rest on the three studs [3].

OPTIONAL ACCESSORIES

- If the fixture was ordered with optional accessories, such as a center disc [6] or ring [7], the main fixture shell [1] will have small aircraft cable tethers [4, 5] pre-attached.
- Short tethers [4] are used with center discs [6]. Slide each tether through a slot on the edge of the disc. The disc rests on the balls on the ends of the tethers.
- Long tethers [5] are used with rings [7]. Slide each tether through a slot on the edge of the ring. The ring rests on the balls on the ends of the tethers.

